

# Signaling Gateway Client Release Notes

Part No. 4-1970-0001-01

For Release 1.9.7

Oct 24, 2018



**Restrictions:** This document contains proprietary information that is protected by copyright; it is intended for your internal use only, it is not to be disclosed to third parties. All rights reserved. No part of this document may be photocopied or reproduced in any way without the prior written permission of NewNet Communication Technologies, LLC. The information contained in this document is subject to change without notice. NewNet makes no warranty of any kind with regard to this material. NewNet shall not be liable for errors contained herein or for incidental

or consequential damages in connection with the use of this material.

## **TRADEMARKS**

NewNet® and AccessMANAGER® are registered trademarks of NewNet Communication Technologies, LLC.

NewNet AccessMANAGER™, NewNet Connect7™, NewNet Distributed7™, NewNet Easy7™, NewNet SG™, NewNet SGC™, NewNet OTAserver™ and NewNet SMserver™ are trademarks of NewNet Communication Technologies, LLC. Sun™, Sun-3™, Sun-4™, Sun386i™, SunInstall™, SunOS™, and SPARC Sun Microsystems™, and Sun Workstations™ are trademarks of Sun Microsystems, Inc.

SPARC® is a registered trademark of SPARC International, Inc. SPARC CPU-2CE™ is a trademark of SPARC International, Inc. licensed to FORCE COMPUTERS, Inc. Solaris® is a registered trademark of Sun Microsystems, Inc. Motorola® and the Motorola logo are registered trademarks of Motorola, Inc. in the U.S.A. and other countries. FX Series™ is a trademark of Motorola Computer Group. AIX®, PowerPC®, RS/6000®, and ARTIC960® are registered trademarks of IBM, Inc. UNIX® is a registered trademark of UNIX Systems Laboratories, Inc. in the U.S.A. and other countries. All the brand names and other products or services mentioned in this document are identified by the trademarks or service marks of their respective companies or organizations.

## **SUCCESSOR IN INTEREST**

NewNet Communication Technologies, LLC is the successor in interest to EBS, Inc.; NewNet, Inc.; ADC Enhanced Services Division; ADC ESD, Inc.; and Centigram Communications Corporation. Any rights or title to the marks or copyrights of these entities, unless otherwise disclosed, are the property of NewNet Communication Technologies, LLC.

## **NOTICES AND WARRANTY INFORMATION**

The information in this document is subject to change without notice and should not be construed as commitment by NewNet Communication Technologies, LLC assumes no responsibility or makes no warranties for any errors that may appear in this document and disclaims any implied warranty of merchantability or fitness for a particular purpose.

## **COPYRIGHT INFORMATION**

### **Signaling Gateway**

The software and design described in this document is furnished under a license agreement. No part of this document may be used or copied in any form or any means without any accordance with the terms of such license or prior written consent of NewNet Communication Technologies, LLC.

### **CMU SNMP**

Copyright © 1988, 1989, 1991, 1992 by Carnegie Mellon University—All Rights Reserved

Permission to use, copy, modify, and distribute this software and its documentation for any purpose and without fee is hereby granted, provided that the above copyright notice appear in all copies and that both that copyright notice and this permission notice appear in supporting documentation, and that the name of CMU not be used in advertising or publicity pertaining to distribution of the software without specific, written prior permission.

CMU DISCLAIMS ALL WARRANTIES WITH REGARD TO THIS SOFTWARE, INCLUDING ALL IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS, IN NO EVENT SHALL CMU BE LIABLE FOR ANY SPECIAL, INDIRECT OR CONSEQUENTIAL DAMAGES OR ANY DAMAGES WHATSOEVER RESULTING FROM LOSS OF USE, DATA OR PROFITS, WHETHER IN AN ACTION OF CONTRACT, NEGLIGENCE OR OTHER TORTIOUS ACTION, ARISING OUT OF OR IN CONNECTION WITH THE USE OR PERFORMANCE OF THIS SOFTWARE.

### **SNMP SMIC**

Copyright © 1992 SynOptics Communications, Inc. All Rights Reserved.

SynOptics grants a non-exclusive license to use, copy, modify, and distribute this software for any purpose and without fee, provided that this copyright notice and license appear on all copies and supporting documentation. SynOptics makes no representations about the suitability of this software for any particular purpose. The software is supplied "AS IS", and SynOptics makes no warranty, either express or implied, as to the use, operation, condition, or performance of the software. SynOptics retains all title and ownership in the software.

**TCL/TK**

This software is copyrighted by the Regents of the University of California; Sun Microsystems, Inc.; and other parties. The following terms apply to all files associated with the software unless explicitly disclaimed in individual files.

The authors hereby grant permission to use, copy, modify, distribute, and license this software and its documentation for any purpose, provided that existing copyright notices are retained in all copies and that this notice is included verbatim in any distributions. No written agreement, license, or royalty fee is required for any of the authorized uses. Modifications to this software may be copyrighted by their authors and need not follow the licensing terms described here, provided that the new terms are clearly indicated on the first page of each file where they apply.

IN NO EVENT SHALL THE AUTHORS OR DISTRIBUTORS BE LIABLE TO ANY PARTY FOR DIRECT, INDIRECT, SPECIAL, INCIDENTAL, OR CONSEQUENTIAL DAMAGES ARISING OUT OF THE USE OF THIS SOFTWARE, ITS DOCUMENTATION, OR ANY DERIVATIVES THEREOF, EVEN IF THE AUTHORS HAVE BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGE.

THE AUTHORS AND DISTRIBUTORS SPECIFICALLY DISCLAIM ANY WARRANTIES, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, AND NON-INFRINGEMENT. THIS SOFTWARE IS PROVIDED ON AN "AS IS" BASIS, AND THE AUTHORS AND DISTRIBUTORS HAVE NO OBLIGATION TO PROVIDE MAINTENANCE, SUPPORT, UPDATES, ENHANCEMENTS, OR MODIFICATIONS.

GOVERNMENT USE: If you are acquiring this software on behalf of the U.S. government, the Government shall have only "Restricted Rights" in the software and related documentation as defined in the Federal Acquisition Regulations (FARs) in Clause 52.227.19 (c) (2). If you are acquiring the software on behalf of the Department of Defense, the software shall be classified as "Commercial Computer Software" and the Government shall have only "Restricted Rights" as defined in Clause 252.227-7013 (c) (1) of DFARs. Notwithstanding the foregoing, the authors grant the U.S. Government and others acting in its behalf permission to use and distribute the software in accordance with the terms specified in this license.

**PERFORMANCE SPECIFICATIONS**

NewNet Communication Technologies, LLC reserves all the rights to change the equipment performance specifications stated herein at any time without notice. For OEM components, NewNet Communication Technologies, LLC relies on the specifications supplied by the OEM vendors.

**ALL RIGHTS RESERVED**

*Copyright © 2007 - 2018*

*NewNet Communication Technologies, LLC*

## GENERAL

Signaling Gateway Client (SGC) 1.9.7 has been tested on the following hardware platforms:

Manufacturer	Model	Processor	OS	Bus	Board PCI-X	Board PCIe
Sun	Netra T2xx series	UltraSPARC T2	Solaris 10	PCI-X PCIe	HDC3-PCI	HDCII-LPe  HDC3-LPe
	Fire Vxxx series			PCI-X		
	Netra T5xx series			PCI-X PCIe		
	Netra 20	PCI				
	Netra X4150	Intel Xeon	Solaris 10	PCIe		
	Netra X4250		CentOS 5.2	PCI-X PCIe		
HP	CentOS 6.3		PCI-X PCIe			
	Proliant DL380 G7					
	Proliant ML110 G6					

In case your server type is not listed above, please contact NewNet CT support.

### **REQUIREMENTS:**

- Each SGC host should be equipped with two Ethernet interfaces for the cluster dual LAN, and two Ethernet interfaces for SCTP access.
- Each pair of redundant Ethernet interfaces should connect to different Ethernet hubs on different subnets to prevent single-point-of-failures.
- SGC can be deployed in conjunction with D7 for hybrid applications.

***Note:** Since all critical internal data, including Heartbeat, synchronization, and SS7/SIGTRAN messages are exchanged between the hosts of a distributed cluster in Distributed7 via dedicated dual Ethernet links, it is imperative that identical interface boards, drivers, and speed be used for these Ethernet connections. Ethernet connections/drivers of different types and/or speeds may cause problems, as all the internal messages through those Ethernet links are sent, for high-availability reasons, in parallel, and must be processed at the peer(s) without delay.*

### **SGC 1.9.7 complies with the following standards:**

- ANSI (1992, 1996) MTP, SCCP
- ITU (1993, 1997) MTP, SCCP
- China MTP
- SS7 MTP3-User Adaptation Layer (M3UA), RFC 3332, September 2002
- SS7 MTP3-User Adaptation Layer (M3UA), RFC 4666, September 2006
- M3UA Implementor's Guide, draft-ietf-sigtran-m3ua-implementors-guide-01.txt
- M3UA SG-SG Communication, draft-bidas-sigtran-sgsg-01.txt, September 2002
- Stream Control Transmission Protocol (SCTP), RFC 2960, Oct. 2000
- Stream Control Transmission Protocol (SCTP) Implementor's Guide, draft-ietf-tsvwg-sctpimpguide-06.txt, May 2002

- Stream Control Transmission Protocol (SCTP) Checksum Change, RFC 3309, September 2002
- SNMPv1, RFC 1157
- SNMPv2, RFC 1905, RFC 1906
- Security Architecture for Internet Protocol, RFC 2401
- Site Security Handbook, RFC 2196

## **NEW FEATURES**

### **Enhancements for 1.9.0**

- Significant D7 performance improvements on CentOS/RedHat 6.3
- LKSCTP support added to D7/SG/SGC stack, which provides further performance boost
  - Red Hat Enterprise Linux 6.3, kernel 2.6.32-279.el6.x86\_64
  - CentOS release 6.3, kernel 2.6.32-279.el6.x86\_64

### **Enhancements for 1.8.1**

- Linux operating system support
  - Red Hat Enterprise Linux 6.3, kernel 2.6.32-279.el6.x86\_64
  - CentOS release 6.3, kernel 2.6.32-279.el6.x86\_64

### **Enhancements for 1.8.0**

- Linux operating system support (Simplex only)
  - Red Hat Enterprise Linux 6.3, kernel 2.6.32-279.el6.x86\_64
  - CentOS release 6.3, kernel 2.6.32-279.el6.x86\_64

### **Enhancements for 1.7.5**

- IPv6 Support on Linux

### **Enhancements for 1.7.2**

- Multiple SP support in case Routing Context is missing in the incoming message.
- Red Hat Enterprise Linux AS release 5.5 kernel 2.6.18.194.el5

### **Enhancements for 1.7.1**

- 24 bit PC size for ITU: 24 bit PC size support for ITU has been added

### **Enhancements for 1.7.0**

- IPv6 support
- SG/SGC OAM API

### **Enhancements for 1.6.2**

- None

### **Enhancements for 1.6.1**

- None

### **Enhancements for 1.6.0**

- Support for the Linux operating system
  - Red Hat Enterprise Linux AS release 4 (Nahant Update 6) kernel 2.6.9-67.ELsmp
  - CentOS release 5.2 (Final) kernel 2.6.18-92.1.10.el5

#### **Enhancements for 1.5.10**

- None

#### **Enhancements for 1.5.7**

- M3UA statistics

#### **Enhancements for 1.5.1**

- HDCII-LPe board support for LSL on x86/Sparc platform
- HDCII-LPe board support for HSL on x86/Sparc platform

#### **Signaling Gateway Client 1.5.1**

- Support for the unified SG package for Solaris 8/9/10 (CRSnn16989)
- Support for the SG routes with different priorities in SGC (CRSnn17001)

#### **Signaling Gateway Client 1.5.0**

- Support for Solaris 10
- Support for Solaris 10 native SCTP stack
- Support for SE mode of IPSP
- Support for database to text conversion for SG (CRSnn16891)

#### **Signaling Gateway Client 1.1.1**

- Distributed7 (D7) 1.4.0 support

#### **Signaling Gateway Client 1.1.0**

- cPCI support
- Eight (8) node clustering support
- Explicit Congestion Notification support in SCTP
- Hostname resolution support

#### **Signaling Gateway Client 1.0.0**

- SGC provides SS7 User Part services, such as ISUP, SCCP and TCAP, to IP-based applications, such as the Media Gateway Controller (MGC), or an IP-based Home Location Register (HLR)
- SGC is compatible with any SS7 network that is ANSI/ITU compliant and with any signaling gateways that are IETF SIGTRAN compliant (version 5)
- Signaling messages from the SS7 network are transported to SGC using SCTP over IP or SCTP over UDP
- Messages that arrive at the SGC are translated back to SS7 MTP User Part messages (ISUP, TCAP and SCCP) through the MTP3 User Adaptation (M3UA) layer of the SIGTRAN protocol and the Nodal Interworking Function (NIF). Similarly, MTP3 User Part messages are transported to the SS7 in

the reverse direction

- In general, SGC's M3UA and NIF provide its User Parts with MTP3 services that are offered remotely from an MTP3 layer at the Signaling Gateway. This allows the User Parts to function as if they were using the local MTP3 layer of the SS7 stack
- SGC provides a reliable, scalable and integrated platform of SS7 and SIGTRAN services to the application developers of MTP3 User Parts. Some examples of applications that can be built on top of the SGC are MGC, IP SCP, and IP HLR. These applications can run on the same host as the SGC, on a different host, or they can be distributed across several hosts in a cluster. The SGC supports the TCP/IP protocol to communicate with the user applications. Therefore, the applications can reside on any host that supports TCP/IP
- SGC supports the routing of SS7 traffic through multiple gateways that run in primary/ backup and load sharing modes. SGC maintains the destination parameters for each Signaling Gateway and determines which Signaling Gateway it uses to send a message to a specific Destination Point Code (DPC)
- The ASP informs the M3UA at the SGC of any congestion detected in the local ASP and IP network, and responds according to the MTP3 procedures
- This SGC version only works in the simplex mode and does not provide any redundancy on the SGC level
- Dividing the routing key among different ASs allows the user applications to share the signaling traffic load on more than one SGC



## **OPERATIONAL/PROGRAMMING IMPACTS**

The following items summarize information or changes in this release that impact the operation or programming interface of Signaling Gateway Client.

### **Signaling Gateway Client 1.7.1**

- None

### **Signaling Gateway Client 1.7.0**

- IPv6 support hence ability to configure the endpoints as IPv6 nodes

### **Signaling Gateway Client 1.6.2**

- New parameter “adj” has been added to SGCDPC to be able to interoperate with SG’s that does not send DAVA/DUNA to adjacent ASP’s.

### **Signaling Gateway Client 1.6.1**

- None

### **Signaling Gateway Client 1.6.0**

- None

### **Signaling Gateway Client 1.5.10**

- None

### **Signaling Gateway Client 1.5.1**

- “Priority” field is added in SGCDPC to support SG routes with different priorities, see section 7.5.4 in the Signaling Gateway Client User Manual

### **Signaling Gateway Client 1.5.0**

- The SGC 1.5.0 release uses Distributed7 SCCP, TCAP, and ISUP APIs and MML commands. Please see the API Reference Manual and User Manual for information about any new APIs and MML commands
- Two new managed objects have been added, including SGCIPAS and SGCIPSP to support IPSP mode. Also, some variant fields in SGCASTFC have changed; see 7.5 in the Signaling Gateway Client User Manual

## **DOCUMENTATION**

The following identifies contents for the Signaling Gateway Client 1.9.7 manual set.

- **USER MANUAL** □  
This document is designed for the user, and describes procedures for configuration, operation, and maintenance of the SGC software
- **DEVELOPMENT MANUAL** □  
This document describes the interface between user-designed applications and SGC
- **API REFERENCE MANUAL** □  
This document describes the Distributed7 SCCP, TCAP, and ISUP APIs that are used by SGC

## **KNOWN PROBLEMS**

<b>CR Number</b>	<b>Description</b>	<b>Remarks</b>
CRSnn17590	System freeze under load during Distributed Operation	On Linux RH7.3 platform with 3.10.0-514.26.1.el7.x86_64 kernel the D7 hosts could freeze under high load during the distributed operation

*Note: Please see the README file and/or the BUGS file for a complete list of all reported problems and/or requested enhancements.*

## **COMPATIBILITY**

### **INSTALLATION NOTES**

Please see the Installation chapter of the Signaling Gateway Client User Manual for detailed installation instructions. Signaling Gateway Client 1.9.7 uses:

- NewNet Distributed7 1.9.7 on the Solaris 10 platform
- NewNet Distributed7 1.9.7 on the Linux platform

*Note: Please refer to the D7 1.9.7 Release Notes for further information about supported platforms and patch levels.*

*Note: Please see the README text file for additional installation information that may not be in the manual.*

## ***DOCUMENTATION UPDATES***

### **1. IPv6 SUPPORT**

#### **IPv6 Support Specifications**

1. IPv6 is supported for Sigtran connectivity.
2. Operation as an IPv4 node is supported for backward compatibility. In this mode D7 SGSGC will behave exactly the same as before IPv6 support. IPv6 infrastructure will not be used and therefore connectivity with IPv6 nodes will not be possible.
3. Different IPv6 address formats are supported: IPv6 long format, IPv6 short format and IPv4 Mapped IPv6 format.
4. When configured as an IPv6 node, connectivity with IPv4 nodes is not possible.
5. Hybrid stack mode is supported. In other words, D7 SGSGC can be configured as an IPv6 node with both an IPv6 address and an IPv4 address (IPv4 Mapped IPv6) to be included in the endpoint so that both IPv6 and IPv4 networks are utilized. In other words, both IPv4 and IPv6 links (mixed) can be used in a multi-homed SCTP association towards a remote peer.

#### **IPv4/IPv6 Configuration**

In order to configure a D7 SGSGC node as an IPv4 node, the local process simply needs to be configured with IPv4 addresses. If even the first of the IP addresses configured for the local process is an IPv6 address in any format then the Sigtran node will be an IPv6 node.

## 2. M3UA Statistics

Below is the help text of the statistics tool.

```
>> m3uastats -h
M3UA Statistics display utility (v1.2)
m3uastats [-h] [-d option] [-c option] [-e option]

-h                print this help and exit
-d all:sum:associd  display data
-c all:associd     clear data (no-arg clears all)
-e export-path     export as csv file.
                  if export-path given: it will override
                  the path setting in the config file.

Examples:

Display data for association-id=2 : m3uastats -d 2
Display data for all associations : m3uastats -d all
Display cumulative data          : m3uastats -d sum
Clear all data (1st way)         : m3uastats -c
Clear all data (2nd way)        : m3uastats -c all
Clear data for association 2     : m3uastats -c 2
Export and clear data           : m3uastats -e -c
Export and not clear data       : m3uastats -e
Export to a directory (don't clear) : m3uastats -e /tmp
Export to a directory (clear)    : m3uastats -e /tmp -c
```

### Note-1:

Exporting to a csv file can also be triggered automatically by the SGC. This can happen either because the periodic csv export functionality is enabled or because a roll-over event (value exceeded the limit) occurred for a parameter. Periodically exporting to a csv file can be enabled by configuring the timer named `oam_m3_stats_tmr` in the `aspd.conf` file. It is by default commented out (value in milliseconds). You can enable this functionality by modifying the `aspd.conf` file.

### Note-2:

New parameters in `aspd.conf` file are explained below. If `aspd.conf` file is modified while SGC is running, USR1 and USR2 signals can be used to force the ASPD process to re-read the configuration parameters.

Timer value in milliseconds for periodic csv export function	<code>oam_m3_stats_tmr</code> (0 means disabled)
Whether or not to clear all statistics data when periodic csv export function is executed	<code>oam_m3_stats_explr</code> (0 means don't clear)
The directory to save the csv file	<code>oam_m3_stats_fpath</code> (default <code>\$SGCHOME/sgc/RUN/m3stats</code> )
These 2 parameters specify the csv filename such that given values produce <code>M3UAStats-112309.csv</code> . Filename format can be manipulated according to the man page. of <code>strftime</code> standard C library function.	<code>oam_m3_stats_fname</code> <code>M3UAStats</code> <code>oam_m3_stats_fname_fmt</code> <code>%m%d%y</code>

**SGC Release Notes**  
**4-1970-0001-01**

---

**Note-3:**

Limits for counters are as below:

TXDATA	9999999999999999
RXDATA	9999999999999999
TXOCTET	9999999999999999
RXOCTET	9999999999999999
TXERR	999999
RXERR	999999
TXDAUD	999999
RXDAVA	999999
RXDUNA	999999
RXDUPU	999999
RXDRST	999999

### 3. SGC OAM API Implementation

Below list of functions are available in SGC OAM library:

-	oam_sgcas()	This function has no former equivalent
-	oam_sgcasp()	This function has no former equivalent
-	oam_sgcastfc()	This function has no former equivalent
-	oam_sgcdpc()	This function has no former equivalent
-	oam_sgcrk()	This function has no former equivalent
-	oam_sgcrkrng()	This function has no former equivalent
-	oam_sgcsq()	This function has no former equivalent
-	oam_sgcsqp()	This function has no former equivalent
-	oam_sgcsqna()	This function has no former equivalent
-	oam_sgqipsp()	This function has no former equivalent
-	oam_sgqipspas()	This function has no former equivalent

#### **Function oam\_sgcas:**

##### **Description**

**oam\_sgcas** Performs a multitude of managed object (MO) related operations on the SGC Application Server (SGCAS) MO including the traffic mode, routing key index and routing context associated with the AS.

*NOTE: This function call must include the <oam\_sgsgc.h> header file.*

##### **MT LEVEL**

MT-Safe

##### **SYNOPSIS**

**int oam\_sgcas(int sp , oam\_oper\_e oper , const oam\_sgcas\_t \* data);**

**sp** This argument specifies the signaling point that is of interest and may assume a value within the [0, 7] range.

**oper** This argument specifies the operation to be performed on the SGCAS MO and may assume a value from the following list:

- E\_OPER\_ADD - Add a new AS configuration to the signaling point specified.
- E\_OPER\_DELETE - Deletes an existing AS configuration for the signalling point specified.
- E\_OPER\_MODIFY - Modify parameters associated with an existing AS configuration.
- E\_OPER\_DISPLAY - Retrieve/display information about the AS configuration specified.
- E\_OPER\_GET\_FIRST - Retrieve/display information about the first instance for the AS configuration specified.
- E\_OPER\_GET\_NEXT - Retrieve/display information about the next AS configuration for the signaling point specified.

**data** This argument points to the user-space buffer of type **oam\_sgcas\_t** which contains information about the AS of interest. Prior to calling the **oam\_sgcas()** function, all appropriate fields within the **oam\_sgcas\_t** structure should be initialized by the application.

### **Function *oam\_sgcasp*:**

#### **Description**

***oam\_sgcasp*** Performs a multitude of managed object (MO) related operations on the SGC Application Server Process (SGCASP) MO. These operations involve modification and display of ASP configured.

*NOTE: This function call must include the <oam\_sgsgc.h> header file.*

#### **MT LEVEL**

MT-Safe

#### **SYNOPSIS**

**int *oam\_sgcasp*(int *sp* , *oam\_oper* , const *oam\_sgcasp\_t* \* *data*);**

***sp*** This argument specifies the signaling point that is of interest and may assume a value within the [0, 7] range.

***oper*** This argument specifies the operation to be performed on the SGCASP MO and may assume a value from the following list:

- E\_OPER\_MODIFY - Modify parameters associated with an existing ASP configuration.
- E\_OPER\_DISPLAY - Retrieve/display information about the ASP configuration specified.
- E\_OPER\_GET\_FIRST - Retrieve/display information about the first instance for the ASP configuration specified.
- E\_OPER\_GET\_NEXT - Retrieve/display information about the next ASP configuration for the signaling point specified.

***data*** This argument points to the user-space buffer of type ***oam\_sgcasp\_t*** which contains information about the ASP of interest. Prior to calling the ***oam\_sgcasp()*** function, all appropriate fields within the ***oam\_sgcasp\_t*** structure should be initialized by the application.

### **Function *oam\_sgcastfc*:**

#### **Description**

***oam\_sgcastfc*** Performs a multitude of managed object (MO) related operations on the SGC Application Server - Application Server Process Traffic Control (SGCASPTFC) MO which defines traffic control for an AS and ASP.

*NOTE: This function call must include the <oam\_sgsgc.h> header file.*

#### **MT LEVEL**

MT-Safe

#### **SYNOPSIS**

**int *oam\_sgcastfc*(int *sp* , *oam\_oper* , const *oam\_sgcas\_t* \* *data*);**

***sp*** This argument specifies the signaling point that is of interest and may assume a value within the [0, 7] range.

***oper*** This argument specifies the operation to be performed on the SGCASTFC MO and may assume a value from the following list:

- E\_OPER\_ADD - Add a new traffic control definition for an AS and ASP to the signaling point specified.
- E\_OPER\_DELETE - Deletes an existing traffic control definition for an AS and ASP for the signalling point specified.
- E\_OPER\_MODIFY - Modify parameters associated with an existing traffic control definition for an AS and ASP.
- E\_OPER\_DISPLAY - Retrieve/display information about the traffic control definition for an AS and ASP.
- E\_OPER\_GET\_FIRST - Retrieve/display information about the first instance for the traffic control definition for an AS and ASP specified.
- E\_OPER\_GET\_NEXT - Retrieve/display information about the next traffic control definition for an AS and ASP for the signaling point specified.

**data** This argument points to the user-space buffer of type **oam\_sgcastfc\_t** which contains information about the traffic control definition for an AS and ASP of interest. Prior to calling the **oam\_sgcastfc()** function, all appropriate fields within the **oam\_sgcastfc\_t** structure should be initialized by the application.

### **Function oam\_sgcdpc:**

#### **Description**

**oam\_sgcdpc** Performs a multitude of managed object (MO) related operations on the SGC Destination Point Code (SGCDPC) MO which defines remote SS7 destination point code that is reachable through a particular SG in a particular network appearance.

*NOTE: This function call must include the <oam\_sgsgc.h> header file.*

#### **MT LEVEL**

MT-Safe

#### **SYNOPSIS**

**int oam\_sgcdpc(int sp , oam\_oper\_e oper , const oam\_sgcdpc\_t \* data);**

**sp** This argument specifies the signaling point that is of interest and may assume a value within the [0, 7] range.

**oper** This argument specifies the operation to be performed on the SGCDPC MO and may assume a value from the following list:

- E\_OPER\_ADD - Add a new point code that an SG can reach to the signaling point specified.
- E\_OPER\_DELETE - Deletes an existing point code that an SG can reach for the signalling point specified.
- E\_OPER\_MODIFY - Modify parameters associated with an existing point code that an SG can reach.
- E\_OPER\_DISPLAY - Retrieve/display information about the point code specified.
- E\_OPER\_GET\_FIRST - Retrieve/display information about the first instance for the point code specified.
- E\_OPER\_GET\_NEXT - Retrieve/display information about the next point code for the signaling point specified.

**data** This argument points to the user-space buffer of type **oam\_sgcdpc\_t** which contains information about the point code that an SG can reach. Prior to calling the **oam\_sgcdpc()** function, all appropriate fields within the **oam\_sgcdpc\_t** structure should be initialized by the application.



### **Function *oam\_sgcrk*:**

#### **Description**

***oam\_sgcrk*** Performs a multitude of managed object (MO) related operations on the SGC Routing Key (SGCRK) MO which defines the route key associated with an AS.

*NOTE: This function call must include the <oam\_sgsgc.h> header file.*

#### **MT LEVEL**

MT-Safe

#### **SYNOPSIS**

**int *oam\_sgcrk*(int *sp* , *oam\_ops\_e* *oper* , const *oam\_sgcrk\_t* \* *data*);**

***sp*** This argument specifies the signaling point that is of interest and may assume a value within the [0, 7] range.

***oper*** This argument specifies the operation to be performed on the SGCRK MO and may assume a value from the following list:

- **E\_OPER\_ADD** - Add a new route key to the signaling point specified.
- **E\_OPER\_DELETE** - Deletes an existing route key for the signalling point specified.
- **E\_OPER\_MODIFY** - Modify parameters associated with an existing route key.
- **E\_OPER\_DISPLAY** - Retrieve/display information about the route key specified.
- **E\_OPER\_GET\_FIRST** - Retrieve/display information about the first instance for the route key specified.
- **E\_OPER\_GET\_NEXT** - Retrieve/display information about the next route key for the signaling point specified.

***data*** This argument points to the user-space buffer of type ***oam\_sgcrk\_t*** which contains information about the route key of interest. Prior to calling the ***oam\_sgcrk()*** function, all appropriate fields within the ***oam\_sgcrk\_t*** structure should be initialized by the application.

### **Function *oam\_sgcrkng*:**

#### **Description**

***oam\_sgcrkng*** Performs a multitude of managed object (MO) related operations on the SGC Routing Key Range (SGCRKNG) MO which defines a range that is associated with an existing route key.

*NOTE: This function call must include the <oam\_sgsgc.h> header file.*

#### **MT LEVEL**

MT-Safe

#### **SYNOPSIS**

**int *oam\_sgcrkng*(int *sp* , *oam\_ops\_e* *oper* , const *oam\_sgcrkng\_t* \* *data*);**

***sp*** This argument specifies the signaling point that is of interest and may assume a value within the [0, 7] range.

***oper*** This argument specifies the operation to be performed on the SGCRKNG MO and may assume a value from the following list:

- **E\_OPER\_ADD** - Add a new routing key range to the signaling point specified.

- E\_OPER\_DELETE - Deletes an existing routing key range for the signalling point specified.
- E\_OPER\_DISPLAY - Retrieve/display information about the routing key range specified.
- E\_OPER\_GET\_FIRST - Retrieve/display information about the first instance for the routing key range specified.
- E\_OPER\_GET\_NEXT - Retrieve/display information about the next routing key range for the signaling point specified.

**data** This argument points to the user-space buffer of type **oam\_sgcrkrng\_t** which contains information about the routing key range of interest. Prior to calling the **oam\_sgcrkrng()** function, all appropriate fields within the **oam\_sgcrkrng\_t** structure should be initialized by the application.

### **Function oam\_sgcsq:**

#### **Description**

**oam\_sgc** Performs a multitude of managed object (MO) related operations on the SGC Signaling Gateway (SGCSG) MO which defines a range that is associated with an existing route key.

*NOTE: This function call must include the <oam\_sgsgc.h> header file.*

#### **MT LEVEL**

MT-Safe

#### **SYNOPSIS**

```
int oam_sgcsq(int sp , oam_oper_e oper , const oam_sgcsq_t * data);
```

**sp** This argument specifies the signaling point that is of interest and may assume a value within the [0, 7] range.

**oper** This argument specifies the operation to be performed on the SGCSG MO and may assume a value from the following list:

- E\_OPER\_ADD - Add a new signaling gateway to the signaling point specified.
- E\_OPER\_DELETE - Deletes an existing signaling gateway for the signalling point specified.
- E\_OPER\_MODIFY - Modify parameters associated with an existing signaling gateway.
- E\_OPER\_DISPLAY - Retrieve/display information about the signaling gateway specified.
- E\_OPER\_GET\_FIRST - Retrieve/display information about the first instance for the signaling gateway specified.
- E\_OPER\_GET\_NEXT - Retrieve/display information about the next signaling gateway for the signaling point specified.

**data** This argument points to the user-space buffer of type **oam\_sgcsq\_t** which contains information about the signaling gateway of interest. Prior to calling the **oam\_sgcsq()** function, all appropriate fields within the **oam\_sgcsq\_t** structure should be initialized by the application.

### **Function *oam\_sgcsgp*:**

#### **Description**

***oam\_sgcsgp*** Performs a multitude of managed object (MO) related operations on the SGC Signaling Gateway Process (SGCSGP) MO.

*NOTE: This function call must include the <oam\_sgsgc.h> header file.*

#### **MT LEVEL**

MT-Safe

#### **SYNOPSIS**

```
int oam_sgcsgp(int sp , oam_ops_e oper , const oam_sgcsgp_t * data);
```

***sp*** This argument specifies the signaling point that is of interest and may assume a value within the [0, 7] range.

***oper*** This argument specifies the operation to be performed on the SGCSGP MO and may assume a value from the following list:

- E\_OPER\_ADD - Add a new signaling gateway process to the signaling point specified.
- E\_OPER\_DELETE - Deletes an existing signaling gateway process for the signalling point specified.
- E\_OPER\_MODIFY - Modify parameters associated with an existing signaling gateway process.
- E\_OPER\_DISPLAY - Retrieve/display information about the signaling gateway process specified.
- E\_OPER\_GET\_FIRST - Retrieve/display information about the first instance for the signaling gateway process specified.
- E\_OPER\_GET\_NEXT - Retrieve/display information about the next signaling gateway process for the signaling point specified.

***data*** This argument points to the user-space buffer of type ***oam\_sgcsgp\_t*** which contains information about the signaling gateway process of interest. Prior to calling the ***oam\_sgcsgp()*** function, all appropriate fields within the ***oam\_sgcsgp\_t*** structure should be initialized by the application.

### **Function *oam\_sgcpna*:**

#### **Description**

***oam\_sgcpna*** Performs a multitude of managed object (MO) related operations on the SGC Signaling Point to Network Appearance Mapping (SGCSPNA) MO.

*NOTE: This function call must include the <oam\_sgsgc.h> header file.*

#### **MT LEVEL**

MT-Safe

#### **SYNOPSIS**

```
int oam_sgcpna(int sp , oam_ops_e oper , const oam_sgcpna_t * data);
```

***sp*** This argument specifies the signaling point that is of interest and may assume a value within the [0, 7] range.

**oper** This argument specifies the operation to be performed on the SGCSPNA MO and may assume a value from the following list:

- E\_OPER\_ADD - Add a new mapping between a Network Appearance and a Signaling Point to the signaling point specified.
- E\_OPER\_DELETE - Deletes an existing mapping between a Network Appearance and a Signaling Point for the signalling point specified.
- E\_OPER\_MODIFY - Modify parameters associated with an existing mapping between a Network Appearance and a Signaling Point.
- E\_OPER\_DISPLAY - Retrieve/display information about the mapping between a Network Appearance and a Signaling Point specified.
- E\_OPER\_GET\_FIRST - Retrieve/display information about the first instance for the mapping between a Network Appearance and a Signaling Point specified.
- E\_OPER\_GET\_NEXT - Retrieve/display information about the next mapping between a Network Appearance and a Signaling Point for the signaling point specified.

**data** This argument points to the user-space buffer of type **oam\_sgcsrna\_t** which contains information about the mapping between a Network Appearance and a Signaling Point. Prior to calling the **oam\_sgcsrna()** function, all appropriate fields within the **oam\_sgcsrna\_t** structure should be initialized by the application.

### **Function oam\_sgciisp:**

#### **Description**

**oam\_sgciisp** Performs a multitude of managed object (MO) related operations on the SGC IP Application Server Process (SGCIPSP) MO.

*NOTE: This function call must include the <oam\_sgsgc.h> header file.*

#### **MT LEVEL**

MT-Safe

#### **SYNOPSIS**

**int oam\_sgciisp(int sp , oam\_oper\_e oper , const oam\_sgciisp\_t \* data);**

**sp** This argument specifies the signaling point that is of interest and may assume a value within the [0, 7] range.

**oper** This argument specifies the operation to be performed on the SGCIPSP MO and may assume a value from the following list:

- E\_OPER\_ADD - Add a new IPSP to the signaling point specified.
- E\_OPER\_DELETE - Deletes an existing IPSP for the signalling point specified.
- E\_OPER\_MODIFY - Modify parameters associated with an existing IPSP.
- E\_OPER\_DISPLAY - Retrieve/display information about the IPSP specified.
- E\_OPER\_GET\_FIRST - Retrieve/display information about the first instance for the IPSP specified.
- E\_OPER\_GET\_NEXT - Retrieve/display information about the next IPSP for the signaling point specified.

**data** This argument points to the user-space buffer of type **oam\_sgciisp\_t** which contains information about the IPSP of interest. Prior to calling the **oam\_sgciisp()** function, all appropriate fields within the **oam\_sgciisp\_t** structure should be initialized by the application.

## **Function *oam\_sgcpas*:**

### **Description**

***oam\_sgcpas*** Performs a multitude of managed object (MO) related operations on the SGC IP Application Server (SGCIPAS) MO.

*NOTE: This function call must include the <oam\_sgsgc.h> header file.*

### **MT LEVEL**

MT-Safe

### **SYNOPSIS**

**int *oam\_sgcpas*(int *sp* , *oam\_oper* *e oper* , const *oam\_sgcpas\_t* \* *data*);**

***sp*** This argument specifies the signaling point that is of interest and may assume a value within the [0, 7] range.

***oper*** This argument specifies the operation to be performed on the SGCIPAS MO and may assume a value from the following list:

- **E\_OPER\_ADD** - Add a new IPAS configuration to the signaling point specified.
- **E\_OPER\_DELETE** - Deletes an existing AS configuration for the signalling point specified.
- **E\_OPER\_MODIFY** - Modify parameters associated with an existing AS configuration.
- **E\_OPER\_DISPLAY** - Retrieve/display information about the AS configuration specified.
- **E\_OPER\_GET\_FIRST** - Retrieve/display information about the first instance for the AS configuration specified.
- **E\_OPER\_GET\_NEXT** - Retrieve/display information about the next AS configuration for the signaling point specified.

***data*** This argument points to the user-space buffer of type ***oam\_sgcpas\_t*** which contains information about the IPAS of interest. Prior to calling the ***oam\_sgcpas()*** function, all appropriate fields within the ***oam\_sgcpas\_t*** structure should be initialized by the application.

## Resolved CRs

### 1.9.7

#### **CRSnn17603 aspdc connection audit timer could stop if the audit thread fails**

**Detailed Description** aspdc connection audit timer could stop if the audit thread fails

**Solution** Aspdc audit timer restart is taken out of the audit thread and placed in the timer handler routine

**Programming Impacts** None

**Operational Impacts** None

**Documentation Impacts** None

**MML Help Text Impact** None

**MO and DB File Impact** None

#### **CRSnn17589 LKSCTP is made default for Linux releases**

**Detailed Description** SCTP robustness is required to be improved

**Solution** LKSCTP is made default option for Linux releases

**Programming Impacts** None

**Operational Impacts** None

**Documentation Impacts** None

**MML Help Text Impact** None

**MO and DB File Impact** None

### 1.9.6

#### **CRSnn17585 2048 IPSP Support**

**Detailed Description** Earlier Releases support 255 IPSP connections

**Solution** SG/SGC processes are enhanced to support 2048 IPSP connections.

**Programming Impacts** None

**Operational Impacts** None

**Documentation Impacts** None

**MML Help Text Impact** None

**MO and DB File Impact** None

### 1.9.5

#### **CRSnn17566 enable adding own pc for another sp**

**Detailed Description** aspd process does not allow to config point codes of own SP. And it was not possible to route a message from one SP towards another SP over the Sigtran network.

**Solution** aspd process is modified to allow its own point codes as sgdcpc's.

**Programming Impacts** None

**Operational Impacts** None

**Documentation Impacts** None

**MML Help Text Impact** None

**MO and DB File Impact** None

**CRSnn17446**      **fix c7 sgc package for lnx**

**Detailed Description** C7 sg/sgc package was not being installed properly.

**Solution** C7 sg/sgc installation scripts are corrected to install successfully.

**Programming Impacts** None

**Operational Impacts** None

**Documentation Impacts** None

**MML Help Text Impact** None

**MO and DB File Impact** None

**CRSnn17569**      **priority based forwarding**

**Detailed Description** Aspd process routes messages over the highest priority sgp which is reachable via the local host. It does not take into consideration higher priority sgp's defined on the other aspd processes within the cluster.

**Solution** When this functionality is enabled the aspd process routes messages over the highest priority sgp on the cluster. In order not to break the backward compatibility in operations the oam\_m3\_prio\_forwarding flag in the aspd.conf file must be set to 1.

**Programming Impacts** None

**Operational Impacts** The oam\_m3\_prio\_forwarding field in the aspd.conf file must be set to 1 to activate this functionality before starting the aspd process.

**Documentation Impacts** None

**MML Help Text Impact** None

**MO and DB File Impact** None

**CRSnn17576**      **move msgs on the fd quickly to internal queues and handle processing in a separete thread.**

**Detailed Description** Under burst situations the connection between the Gateway\_X connection aspd/sgpd process and the upm driver was getting congested.

**Solution** Preventive solutions are implemented to avoid the congextion between the aspd/sgpd process and the upm driver

**Programming Impacts** None

**Operational Impacts** None

**Documentation Impacts** None

MML Help Text Impact None  
MO and DB File Impact None

**CRSnn17579 Double association guard timer startedvi**

**Detailed Description** The double sctp association guard timers could cause association state corruption after associations bounce

**Solution** This problem is fixed in the SG/SGC code to handle the sctp association guard timers properly in case of association bounce.

**Programming Impacts** None

**Operational Impacts** None

**Documentation Impacts** None

**MML Help Text Impact** None

**MO and DB File Impact** None

**1.9.4**

**CRSnn17545 New aspd.conf parameters for flexible SLS usage**

**Detailed Description** Customer needs flexible SLS usage in SG/SGP selection.

**Solution** New configuration parameters are available to have flexible SLS usage in selecting sg/sgp.  
oam\_m3\_sls\_sg\_div - sls divider used when selecting the SG (default 1)  
oam\_m3\_sls\_sgp\_div - sls divider used when selecting the SGP (default 1)

**Programming Impacts** None

**Operational Impacts** None

**Documentation Impacts** None

**MML Help Text Impact** None

**MO and DB File Impact** None

**CRSnn17546 ASPD crash**

**Detailed Description** ASPD process crashes with a single SCTP stream.

**Solution** Bug fix implemented to be able to work with single stream.

**Programming Impacts** None

**Operational Impacts** None

**Documentation Impacts** None

**MML Help Text Impact** None

**MO and DB File Impact** None

**CRSnn17556 fPIC option required for OAM library on Linux**

**Detailed Description** fPIC option needed for the OAM library.



**Solution** New build option added for fPIC.

**Programming Impacts** None

**Operational Impacts** None

**Documentation Impacts** None

**MML Help Text Impact** None

**MO and DB File Impact** None

### **CRSnn17557 RCID exclude/ignore functionality**

**Detailed Description** New configuration parameter for RCID exclude/ignore functionality.

**Solution** Parameter name: oam\_m3\_rcid\_exclude\_ignore. If set to zero, normal behavior (default 0).  
If set to one: RCID is not included in outgoing messages, and ignored in the incoming messages.

**Programming Impacts** None

**Operational Impacts** None

**Documentation Impacts** None

**MML Help Text Impact** None

**MO and DB File Impact** None

### **1.9.3**

**None**

### **1.9.2**

### **CRSnn17449 SCTPD core dumps during shutdown**

**Detailed Description** SCTPD daemon dumps core intermittently during shutdown on Linux.

**Solution** Bug fix implemented to nullify endpoint pointers during shutdown.

**Programming Impacts** None

**Operational Impacts** None

**Documentation Impacts** None

**MML Help Text Impact** None

**MO and DB File Impact** None

### **CRSnn17506 Accept ASPAC-Ack without traffic mode**

**Detailed Description** Traffic mode parameter is optional in ASPAC-Ack message.

**Solution** Fix has been implemented to accept ASPAC-Ack message without the traffic mode parameter.

**Programming Impacts** None

**Operational Impacts** None  
**Documentation Impacts** None  
**MML Help Text Impact** None  
**MO and DB File Impact** None

**CRSnn17509      Too many Sigtran gateway registration error logs**

**Detailed Description** Gateway registration attempts fail but the retries are done without a sleep causing too many error logs.

**Solution** Fix has been implemented to sleep 1 second between retries.

**Programming Impacts** None  
**Operational Impacts** None  
**Documentation Impacts** None  
**MML Help Text Impact** None  
**MO and DB File Impact** None

**1.9.1**

**CRSnn16991      Optional aspid in aspup-ack**

**Detailed Description** ASPID in ASPUP-Ack is optional in RFC 4666.

**Solution** Accept ASPID in ASPUP-Ack.

**Programming Impacts** None  
**Operational Impacts** None  
**Documentation Impacts** None  
**MML Help Text Impact** None  
**MO and DB File Impact** None

**CRSnn17315      log the message discard events at SCTP**

**Detailed Description** Log message discard events due to congestion.

**Solution** New log added.

**Programming Impacts** None  
**Operational Impacts** None  
**Documentation Impacts** None  
**MML Help Text Impact** None  
**MO and DB File Impact** None

**CRSnn16991      DAVA/DUNA handling doesn't work with no-na no-rc**

**Detailed Description** DPC not becoming accessible even after DAVA.

**Solution** DAVA/DUNA processing has been fixed for the no-na no-rc case.

**Programming Impacts** None  
**Operational Impacts** None  
**Documentation Impacts** None  
**MML Help Text Impact** None  
**MO and DB File Impact** None

**CRSnn17467**      **SG deadlock**

**Detailed Description** SGPD process gets stuck during association fluctuations.

**Solution** Deadlock scenario has been prevented.

**Programming Impacts** None  
**Operational Impacts** None  
**Documentation Impacts** None  
**MML Help Text Impact** None  
**MO and DB File Impact** None

**1.9.0**

**CRSnn17455**      **aspia-ack behavior corrected**

**Detailed Description** If the ASP receives an ASP Inactive Ack without having sent an ASP Inactive message, the ASP should now consider itself to be in the ASP-INACTIVE state. But D7 simply ignores the ASPIA-ack.

**Solution** ASPIA-ack behavior is corrected.

**Programming Impacts** None  
**Operational Impacts** None  
**Documentation Impacts** None  
**MML Help Text Impact** None  
**MO and DB File Impact** None

**CRSnn16991**      **SGPD process dumps core**

**Detailed Description** SGPD process dumps core intermittently.

**Solution** Root cause found as uninitialized variable and fix provided.

**Programming Impacts** None  
**Operational Impacts** None  
**Documentation Impacts** None  
**MML Help Text Impact** None  
**MO and DB File Impact** None

**CRSnn17315**      **LKSCTP support**

**Detailed Description** LKSCTP supportLKSCTP support needed on Linux platforms.  
**Solution** LKSCTP support has been added to D7/SG/SGC.

**Programming Impacts** None  
**Operational Impacts** None  
**Documentation Impacts** None  
**MML Help Text Impact** None  
**MO and DB File Impact** None

**1.8.1**

**CRSnn17446**      **sg(c)\_setrelease problems**

**Detailed Description** 1.8.0 has a bug in sg(c)\_setrelease scripts for downgrade.  
**Solution** Bug fix implemented.

**Programming Impacts** None  
**Operational Impacts** None  
**Documentation Impacts** None  
**MML Help Text Impact** None  
**MO and DB File Impact** None

**1.8.0**

**CRSnn17439**      **IPSP reroute messages**

**Detailed Description** Sigtran traffic in IPSP mode should reach the destination even if the destination is only reachable via another cluster node.  
**Solution** Rerouting message support has been added for IPSP mode.

**Programming Impacts** None  
**Operational Impacts** None  
**Documentation Impacts** None  
**MML Help Text Impact** None  
**MO and DB File Impact** None

**CRSnn17446**      **Restricted D7 package Changes**

**Detailed Description** D7 will support restricted packages for non-root operation.  
**Solution** Support for non-root operation with no setuid has been implemented.

**Programming Impacts** None  
**Operational Impacts** None  
**Documentation Impacts** None  
**MML Help Text Impact** None  
**MO and DB File Impact** None

**CRSnn17447**      **daud problem for some destinations**

**Detailed Description** SGC does not send DAUD for some destinations in case of multiple stacks using the same NAID.

**Solution** Bug found and fixed in the M3UA library.

**Programming Impacts** None  
**Operational Impacts** None  
**Documentation Impacts** None  
**MML Help Text Impact** None  
**MO and DB File Impact** None

**CRSnn17448**      **aspac-ack problem with no-rc**

**Detailed Description** SGC sends back error in response to ASPAC-Ack.

**Solution** In case of no RC in the ASPAC-Ack and multiple inactive AS's at the time of the message reception, error is returned. This behavior is fixed.

**Programming Impacts** None  
**Operational Impacts** None  
**Documentation Impacts** None  
**MML Help Text Impact** None  
**MO and DB File Impact** None

**1.7.7**

**CRSnn17428**      **IPv6 fix for Linux**

**Detailed Description** Sigtran stack not coming up using IPv4 when the IPv6 stack is disabled.

**Solution** Bug found and fixed in the NewNet SCTP stack.

**Programming Impacts** None  
**Operational Impacts** None  
**Documentation Impacts** None  
**MML Help Text Impact** None  
**MO and DB File Impact** None

**CRSnn17431**      **IPv6 MTU fix for Linux**

**Detailed Description** Sigtran stack not working with IPv6.  
**Solution** Bug found related with reading the correct MTU values, which is hit only under certain IPv4/IPv6 address combinations on a system.  
**Programming Impacts** None  
**Operational Impacts** None  
**Documentation Impacts** None  
**MML Help Text Impact** None  
**MO and DB File Impact** None

**1.7.6**

**CRSnn17391**      **ASPD deadlock**

**Detailed Description** Incorrect SIGPOLL handling in the ASPD process caused a deadlock.  
**Solution** SIGPOLL handling has been fixed.  
**Programming Impacts** None  
**Operational Impacts** None  
**Documentation Impacts** None  
**MML Help Text Impact** None  
**MO and DB File Impact** None

**CRSnn17308**      **Race among SCTP timers**

**Detailed Description** Previous fix in 1.7.1 has been improved.  
**Solution** IDLE state also protected in the timer timeout handling process.  
**Programming Impacts** None  
**Operational Impacts** None  
**Documentation Impacts** None  
**MML Help Text Impact** None  
**MO and DB File Impact** None

**CRSnn17418**      **Incorrect handling of MTP3 Congestion test messages**

**Detailed Description** MTP3 Congestion test messages caused incorrect mlogs.  
**Solution** Functionality has been fixed and the mlogs are prevented.  
**Programming Impacts** None  
**Operational Impacts** None  
**Documentation Impacts** None  
**MML Help Text Impact** None  
**MO and DB File Impact** None

**CRSnn17417**

**Periodic DAUD functionality has been added**

**Detailed Description** Sigtran layer is required to send DAUD messages periodically for unreachable remote destinations.

**Solution** Functionality has been implemented in the ASPD process.

**Programming Impacts** None

**Operational Impacts** None

**Documentation Impacts** None

**MML Help Text Impact** None

**MO and DB File Impact** None

**CRSnn17420**

**TFA error handling**

**Detailed Description** In some situations such as congestion or due to too many DAVA messages at the same time, TFA message from Sigtran towards the MTP3 layer may fail. However, in this case the Sigtran destination state stays in Accessible state whereas the MTP3 state stays in Inaccessible state, causing inconsistency between destination availability states among different stack layers.

**Solution** TFA handling has been fixed to handle error conditions as well.

**Programming Impacts** None

**Operational Impacts** None

**Documentation Impacts** None

**MML Help Text Impact** None

**MO and DB File Impact** None

**1.7.5**

**CRSnn17125**

**M3UA Statistics Logs**

**Detailed Description** Minor improvements in mlogs and m3uastats time operation

**Solution** Implemented in the M3UA code.

**Programming Impacts** None

**Operational Impacts** None

**Documentation Impacts** None

**MML Help Text Impact** None

**MO and DB File Impact** None

**CRSnn17366**

**IPv6 Support on Linux**

**Detailed Description** Ipv6 support is requested for Linux Platforms

**Solution** The Ipv6 support has been implemented for Linux platforms also. The MO configuration for IPv6 is the same as the Solaris platforms.

**Programming Impacts** None

**Operational Impacts** None

**Documentation Impacts** None

**MML Help Text Impact** None

**MO and DB File Impact** None

**CRSnn17384**

**Association Setup Problem**

**Detailed Description** An issue is identified in SCTP association setup on Linux platforms.

**Solution** The problem has been identified in the SCTP library and addressed.

**Programming Impacts** None

**Operational Impacts** None

**Documentation Impacts** None

**MML Help Text Impact** None

**MO and DB File Impact** None

**CRSnn17387**

**SCTP Bug**

**Detailed Description** SG/SGC software does not function properly when the remote peers have the same IP address but different ports for SCTP associations.

**Solution** SCTP interface is corrected to handle the same IP different port condition for remote peers properly.

**Programming Impacts** None

**Operational Impacts** None

**Documentation Impacts** None

**MML Help Text Impact** None

**MO and DB File Impact** None

**1.7.4.2**

**CRSnn16991**

**Package ownership issue**

**Detailed Description** The SG/SGC package is not created with the right package ownership flags on Linux platforms.

**Solution** Packageing scripts is corrected to install the SG/SGC packages with the right ownership flags.

**Programming Impacts** None

**Operational Impacts** None

**Documentation Impacts** None

**MML Help Text Impact** None

**MO and DB File Impact** None

**1.7.4.1**

**CRSnn17357**

**SG-SG issue with PC states**

**Detailed Description** SG-SG configurations in distributed mode could experience inconsistent Destination states among the SGP's of the cluster.

**Solution** Destination State synchronization problem among the SGP's of the cluster is fixed.

**Programming Impacts** None

**Operational Impacts** None

**Documentation Impacts** None

**MML Help Text Impact** None



MO and DB File Impact None

### 1.7.4

#### **CRSnn17348 Remote peer state problem**

**Detailed Description** The operation states of remote peers are lost after process restart.

**Solution** Fix provided for the correct handling of database files.

**Programming Impacts** None

**Operational Impacts** None

**Documentation Impacts** None

**MML Help Text Impact** None

**MO and DB File Impact** None

#### **CRSnn17345 Problems with ASPTM exchanges**

**Detailed Description** ASP's internal state is corrupted and ASP activation fails.

**Solution** Bugs are removed that corrupts ASP's internal tables.

**Programming Impacts** None

**Operational Impacts** None

**Documentation Impacts** None

**MML Help Text Impact** None

**MO and DB File Impact** None

### 1.7.3

#### **CRSnn17343 Invalid ASPID problem**

**Detailed Description** ASPD returns "invalid aspid" error for "mod-sgcasp" command even though the ASP is a member of the cluster.

**Solution** Fix implemented in the process list handling of ASP.

**Programming Impacts** None

**Operational Impacts** None

**Documentation Impacts** None

**MML Help Text Impact** None

**MO and DB File Impact** None

#### **CRSnn17344 SNMP fixes**

**Detailed Description** Various MO's are returned incorrectly via SNMP.

**Solution** Fixes are implemented for SNMP functionality.

**Programming Impacts** None

**Operational Impacts** None

**Documentation Impacts** None

**MML Help Text Impact** None

MO and DB File Impact None

## 1.7.2

### **CRSnn17321 SGC core dump in IPSP operation**

**Detailed Description** ASPD core dumps due to a bug while operating as IPSP.

**Solution** Fix the bug to prevent core dumps.

**Programming Impacts** None

**Operational Impacts** None

**Documentation Impacts** None

**MML Help Text Impact** None

**MO and DB File Impact** None

### **CRSnn17324 Invalid length message handling improved**

**Detailed Description** ASPD goes into infinite loop when a message with invalid length is received.

**Solution** Implement necessary corrections in message handling logic.

**Programming Impacts** None

**Operational Impacts** None

**Documentation Impacts** None

**MML Help Text Impact** None

**MO and DB File Impact** None

### **CRSnn17332 SGP load sharing problem**

**Detailed Description** Load sharing doesn't work correctly when there are more than 4 SGP's per SG.

**Solution** Fix the load sharing logic.

**Programming Impacts** None

**Operational Impacts** None

**Documentation Impacts** None

**MML Help Text Impact** None

**MO and DB File Impact** None

### **CRSnn17334 Optional Routing Context with multiple SP's**

**Detailed Description** D7 with multiple SP's needs to be interoperable with remote peers which doesn't send RC.

**Solution** DPC field in the incoming messages is used to route incoming messages towards the correct SP's.

**Programming Impacts** None

**Operational Impacts** None

**Documentation Impacts** Yes.

**MML Help Text Impact** Yes.

**MO and DB File Impact** None

**CRSnn17335**

**alarmd core dumps**

**Detailed Description** ASPD leaks memory when SGCHOME is not set.  
**Solution** Fix the unhandled boundary condition in the M3UA library.

**Programming Impacts** None  
**Operational Impacts** None  
**Documentation Impacts** None  
**MML Help Text Impact** None  
**MO and DB File Impact** None

**CRSnn17337**

**RTSET/SGCDPC problem**

**Detailed Description** Destination accessibility state cannot be recovered in the cluster after D7 shutdown on a host.  
**Solution** Improve the ASPD and UPM driver shutdown process such that the race window in the UPM state machine is reduced during D7 shutdown.

**Programming Impacts** None  
**Operational Impacts** None  
**Documentation Impacts** None  
**MML Help Text Impact** None  
**MO and DB File Impact** None

**CRSnn17338**

**MS bit set only for optional NAID**

**Detailed Description** It is required that different values can be set for NAID and still it is not sent across the network.  
**Solution** Previously NAID was required to be set as 0xFFFFFFFF (i.e. 4294967295 or -1) when it shouldn't be sent. Now setting only the most significant bit to 1 will be sufficient, which is backwards compatible as well.

**Programming Impacts** None  
**Operational Impacts** None  
**Documentation Impacts** Yes.  
**MML Help Text Impact** Yes.  
**MO and DB File Impact** None

**1.7.1**

**CRSnn17308**

**Some associations don't come up after network issues**

**Detailed Description** Some associations don't come up under certain conditions.  
**Solution** Fix the race among the timers.

**Programming Impacts** None  
**Operational Impacts** None  
**Documentation Impacts** None  
**MML Help Text Impact** None  
**MO and DB File Impact** None

**CRSnn17314**

**24 bit ITU support on SGSGC**

<b>Detailed Description</b>	24 bit point code support for ITU
<b>Solution</b>	Implement the new functionality as requested.
<b>Programming Impacts</b>	None
<b>Operational Impacts</b>	None
<b>Documentation Impacts</b>	None
<b>MML Help Text Impact</b>	None
<b>MO and DB File Impact</b>	None

### 1.7.0

#### **CRSnn17217**      **SG/SGC OAM API**

<b>Detailed Description</b>	An SG/SGC OAM API is requested by the customer.
<b>Solution</b>	An implementation of SG/SGC OAM API will be provided.
<b>Programming Impacts</b>	None
<b>Operational Impacts</b>	None
<b>Documentation Impacts</b>	None
<b>MML Help Text Impact</b>	None
<b>MO and DB File Impact</b>	None

#### **CRSnn17225**      **IPv6 Support for SIGTRAN connectivity**

<b>Detailed Description</b>	IPv6 will be supported for SIGTRAN connectivity.
<b>Solution</b>	The implementation will be backward compatible with IPv4 operation. Different IPv6 address formats will be supported (IPv6 long format, IPv6 short format and IPv4 mapped IPv6 format).
<b>Programming Impacts</b>	None
<b>Operational Impacts</b>	None
<b>Documentation Impacts</b>	None
<b>MML Help Text Impact</b>	None
<b>MO and DB File Impact</b>	None

#### **CRSnn17226**      **Problem adding SGP's**

<b>Detailed Description</b>	Customer experienced a problem during MML operations to add new remote processes..
<b>Solution</b>	Bug in our M3UA library to be fixed.
<b>Programming Impacts</b>	None
<b>Operational Impacts</b>	None
<b>Documentation Impacts</b>	None
<b>MML Help Text Impact</b>	None
<b>MO and DB File Impact</b>	None

**CRSnn17256      Incorrect audit on SGC**

**Detailed Description**      Customer complains about SGC sending an extra audit message when a new DPC is added.

**Solution**      Bug in our M3UA library to be fixed.

**Programming Impacts**      None

**Operational Impacts**      None

**Documentation Impacts**      None

**MML Help Text Impact**      None

**MO and DB File Impact**      None

## 1.6.2

### **CRSnn17222**      **Problem connecting with Siemens SG**

**Detailed Description** Problem arises when the SGC sends a DAUD message with the affected SPC point code. D7/SGC needs a DAVA message to be received in order to set the SPC point code as "accessible", but the Siemens SG does not send either a DAVA or a DUNA message. According to Siemens, the DAUD message is only needed for remote SPC, i.e. SS7 point codes that are beyond the SG.

**Solution** The RFC 4666 in section 3.4.3 says:  
The DAUD message MAY be sent from the ASP to the SGP to audit the availability/congestion state of SS7 routes from the SG to one or more affected destinations.  
Consequently D7/SGC should not need a DAVA message to be received from the SG as it's and adjacent point code. From our point of view, the SPC of the adjacent Signaling Gateway should be treated as accessible by the SGC, as soon as the SG is available from an M3UA pint of view.  
The required modifications are:  
1. New field for SGCDPC MO to indicate an adjacent PC; hence modifications for OAM tables and functions to accommodate this change.  
2. Modifications in our M3UA library to alter the PC activation logic.  
3. Modifications in db2date and db2text to accommodate the new field.

**Programming Impacts** None  
**Operational Impacts** None  
**Documentation Impacts** None  
**MML Help Text Impact** None  
**MO and DB File Impact** None

### **CRSnn17221**      **Default bash shell script setup**

**Detailed Description** Bash profile is not being sourced when switching to sgadm/ascadm user.

**Solution** “.bash\_profile” script will be created instead of “.bashrc” during installation.

**Programming Impacts** None  
**Operational Impacts** None  
**Documentation Impacts** None  
**MML Help Text Impact** None  
**MO and DB File Impact** None

**CRSnn17218**      **rtset-sgcdpc inconsistency and SCON handling**

<b>Detailed Description</b>	M3UA PAUSE/RESUME indications are not created even though the only 2 associations towards a DPC are going down/up. M3UA layer accepts DAVA/DUNA messages from SG's even though they are not defined via MML.  Remote SGP sends high load of SCON messages even if they are with the same congestion level. All of these SCON messages are sent upwards to UPM from M3UA layer. This can cause congestion at the upper layers.
<b>Solution</b>	Modify SGC such that only the SG's defined via MML for a DPC can send DAVA/DUNA, the rest is ignored. Also configurable behavior via the configuration file. Modify SCON handling such that there is an inhibit period of 2 seconds in which SCON messages with the same congestion level are ignored.
<b>Programming Impacts</b>	None
<b>Operational Impacts</b>	None
<b>Documentation Impacts</b>	None
<b>MML Help Text Impact</b>	None
<b>MO and DB File Impact</b>	None

**CRSnn17215**      **SCTP timer array size is not sufficient**

<b>Detailed Description</b>	SCTP timer array size is not sufficient for the customer's configuration.
<b>Solution</b>	Increased the SCTP timer array size
<b>Programming Impacts</b>	None
<b>Operational Impacts</b>	None
<b>Documentation Impacts</b>	None
<b>MML Help Text Impact</b>	None
<b>MO and DB File Impact</b>	None

**CRSnn17203**      **ASP and IPSP role on SGC on the same SP**

<b>Detailed Description</b>	Customer needs to be able to connect to both SGP's and IPSP's on an SGC deployment on the same SP.
<b>Solution</b>	Implemented the necessary modifications on SGC.
<b>Programming Impacts</b>	None
<b>Operational Impacts</b>	None
<b>Documentation Impacts</b>	None
<b>MML Help Text Impact</b>	None
<b>MO and DB File Impact</b>	None

**CRSnn17202**      **db2date compatibility problem**

<b>Detailed Description</b>	Customer needs to be able to connect to both SGP's and IPSP's on an SGC deployment on the same SP.
<b>Solution</b>	Implemented the necessary modifications on SGC.
<b>Programming Impacts</b>	None
<b>Operational Impacts</b>	None
<b>Documentation Impacts</b>	None
<b>MML Help Text Impact</b>	None
<b>MO and DB File Impact</b>	None

**1.5.10**

**CRSnn17212**      **High CPU usage by sgpd/aspd**

<b>Detailed Description</b>	CPU usage increases due to the high number of messages on the _aspd queue which is visible in hat_collects and alarmlogs.
<b>Solution</b>	Ensure any outstanding PC_STATE indications are sent first before forwarding a message. Ensure a message cannot be forwarded multiple times among the hosts. Add new mlogs to understand the SPMC table states on the cluster hosts in terms of PC reachability.
<b>Programming Impacts</b>	None
<b>Operational Impacts</b>	None
<b>Documentation Impacts</b>	None
<b>MML Help Text Impact</b>	None
<b>MO and DB File Impact</b>	None

**CRSnn17213**      **sctpd.conf path logic modified**

<b>Detailed Description</b>	Enable to run aspd/sgpd without using sgcadm and sgadm users. Allow aspd to look for SGCHOME and sgpd to look for SGHOME when trying to determine the path of the sctpd.conf file. Currently SGHOME is checked and then if it is null, SGCHOME is checked.
<b>Solution</b>	Modify the logic which determines the path of the sctpd.conf file.
<b>Programming Impacts</b>	None
<b>Operational Impacts</b>	None
<b>Documentation Impacts</b>	None
<b>MML Help Text Impact</b>	None
<b>MO and DB File Impact</b>	None



## 1.5.9

### **CRSnn17155**      **Remove deadlock conditions in M3UA**

<b>Detailed Description</b>	Customer experiences MML timeouts during SGC configuration, even for display commands such as d-sgcdpc;
<b>Solution</b>	Removed deadlock conditions in M3UA.
<b>Programming Impacts</b>	None
<b>Operational Impacts</b>	None
<b>Documentation Impacts</b>	None
<b>MML Help Text Impact</b>	None
<b>MO and DB File Impact</b>	None

### **CRSnn17145**      **M3UA statistics add-on**

<b>Detailed Description</b>	<p>D7-R1x-STAT-010: It shall be possible to define the name for the statistics file, including date/time in the file name defined by applying YYYY, MM, DD, hh, mm, ss as wildcard and in any order.</p> <p>D7-R1x-STAT-020: The full path for the statistics file can be configured in aspd.conf.</p> <p>D7-R1x-STAT-030: The export to CSV should not clear statistics in each case as defined by parameter -e. It shall be possible to define, if the statistics will be cleared when exporting to CSV. Parameter -e shall export data to CSV only and not clear the statistics.</p> <p>D7-R1x-STAT-031: The combined parameter -e for exporting data to CSV shall export statistics and clear them if used with -c parameter. E.g. # m3uaststs -e -c</p>
<b>Solution</b>	Added the necessary functionalities.
<b>Programming Impacts</b>	None
<b>Operational Impacts</b>	None
<b>Documentation Impacts</b>	None
<b>MML Help Text Impact</b>	None
<b>MO and DB File Impact</b>	None

## 1.5.8

### **CRSnn17142**      **Master ASPD assignment improved**

<b>Detailed Description</b>	The ASPD process tries to become master for only three (3) seconds, and this is not enough for a heavily configured 4-host cluster. Due to a forced shutdown of the D7 stack, the shutdown process takes up to 30 seconds
<b>Solution</b>	Made the retry interval 300 seconds.
<b>Programming Impacts</b>	None
<b>Operational Impacts</b>	None
<b>Documentation Impacts</b>	None
<b>MML Help Text Impact</b>	None

**MO and DB File Impact** None

### 1.5.7

## **CRSnn17125**      **M3UA statistics**

**Detailed Description** M3UA statistics should be kept and displayed by the NewNet SIGTRAN stack.

**Solution**

Statistics data is accumulated by SGC, and displayed/cleared/exported by a utility program named 'm3uastats'. It is located in the bin directory of the SGC release. Please use 'm3uastats -h' to see the usage of it.

Examples for m3uastats usage:

```
>> m3uastats -d all # display all statistics data
>> m3uastats -d sum # display cumulative data (sum of data for all associations)
>> m3uastats -d 20003 # display data for association 20003
>> m3uastats -c all # clear all data
>> m3uastats -c 2 # clear data for association 2
>> m3uastats -e # export data to csv file and clear all data
```

Exporting to a csv file can also be triggered automatically by the SGC. This can happen either because the periodic csv export functionality is enabled or because a rollover event (value exceeded the limit) occurred for a parameter. Periodically exporting to a csv file can be enabled by configuring the timer named oam\_m3\_stats\_tmr in the aspd.conf file. It is by default commented out (value in milliseconds). You can enable this functionality by modifying the aspd.conf file.

**Programming Impacts** None

**Operational Impacts** None

**Documentation Impacts** None

**MML Help Text Impact** None

**MO and DB File Impact** None

### 1.5.6

## **CRSnn17106**      **M3UA timers (aspm and aspt)**

**Detailed Description** Entertain request to configure the timer T(ack) as defined in RFC 3332. According to this RFC: "T(ack) is provisionable, with a default of 2 seconds."

**Solution** Enabled ASPM and ASPT timers, and made them configurable.

**Programming Impacts** None

**Operational Impacts** None

**Documentation Impacts** None

**MML Help Text Impact** None

**MO and DB File Impact** None

### **CRSnn17108 Uneven M3UA traffic**

**Detailed Description** It has been reported that some remote peers receive M3UA messages in an uneven manner. At the D7 cluster side: ASP2 creates twice as much outgoing traffic as ASP1 does, and ASP4 creates twice as much outgoing traffic as ASP3 does, towards the remote peers. As a result, one of the assigned ASPs is significantly dominant for each of D7 AS's. Please note that this happens with the LOADSHARE option enabled in Sigtran configuration.

**Solution** Implemented round-robin routing in SGSGC.

**Programming Impacts** None

**Operational Impacts** None

**Documentation Impacts** None

**MML Help Text Impact** None

**MO and DB File Impact** None

### **CRSnn17115 No further attempts to send INIT**

**Detailed Description** SGSGC makes no further attempts (send INIT) to establish an SCTP association after it goes down. There is a bug causing an SPM timer message to get lost, which stops the mechanism that audits SCTP associations.

**Solution** Implemented another mechanism to handle SPM messages, thus eliminating message loss.

**Programming Impacts** None

**Operational Impacts** None

**Documentation Impacts** None

**MML Help Text Impact** None

**MO and DB File Impact** None

## **1.5.3**

### **CRSnn17082 SGCDPC pointcodes set to 0-0-0**

**Detailed Description** SGCDPC pointcodes set to 0-0-0 after upgrade.

**Solution** The problem is caused by memory corruption while growing the SCTP association table for more than ten (10) connections. Previously started SCTP connection timers will use the old memory addresses of associations that are already freed, and then allocated for something else (in the customer's case it's the DPC table). Changed SCTP timer function parameter from assoc to assocId.

**Programming Impacts** None

**Operational Impacts** None

**Documentation Impacts** None

MML Help Text Impact None  
MO and DB File Impact None

## 1.5.2

### **CRSnn17066 Invalid RC in ASPAC messages**

**Detailed Description** Invalid Routing Context encountered in ASP Active messages If the SGP MO is added (or deleted/re-added) after the AS MO is created, traffic status (via sgcastfc) cannot be activated because the existing code doesn't build the necessary link between the AS and SGP tables. This results in both the respective RCID list index in the AS record and the AS indexes in the SGP table not being updated, so the corresponding ASTFC never gets activated.

**Solution** A function has been implmeted to establish the missing link between the SGP and AS tables during add-sgcsgp operation.

**Programming Impacts** None  
**Operational Impacts** None  
**Documentation Impacts** None  
**MML Help Text Impact** None  
**MO and DB File Impact** None

### **CRSnn17067 Association shutdown/restart problem**

**Detailed Description** If the same IP address is configured twice by accident via add-sgcsgp (or add-sgcipsp), different MOs are created with the same IP, causing the SCTP association to fail later with error "Address already in use".

**Solution**

1. Added some checks in the SGCSGP MO (and SGPIPSP) addition, such that the IP address of the new MO is checked against the existing database.
2. When connect() call fails with error "Address already in use", a delete of the existing association is performed (SCTP API provides means to delete the association, even if the corresponding association id is not known).  
The first fix will prevent case 1 from happening, and the second fix will provide a recovery if the OS association is left open during an SGCSGP disconnect because of case 2.

**Programming Impacts** None  
**Operational Impacts** None  
**Documentation Impacts** None  
**MML Help Text Impact** None  
**MO and DB File Impact** None

**CRSnn17069**      **ASTFC state made persistent**

<b>Detailed Description</b>	ASTFC state changes after host restart.
<b>Solution</b>	Added origpid to astfc_rec_t, and modified keysize accordingly.
<b>Programming Impacts</b>	None
<b>Operational Impacts</b>	None
<b>Documentation Impacts</b>	None
<b>MML Help Text Impact</b>	None
<b>MO and DB File Impact</b>	None

**1.5.1**

**CRSnn17037**      **Same NAID for SP's with different protocols**

<b>Detailed Description</b>	Configuring two SP's (one with ITU the other with ANSI) with no NAID (Network Appearance ID) and trying to distinguish the traffic based on routing context fails because SG/SGC doesn't accept different protocols having the same NAID. In this case, both SP's have NAID=4294967295 (0xffffffff) because operating without NAID is configured by setting it to 4294967295 (0xffffffff) and this should work.
<b>Solution</b>	Don't perform the check for protocol equality when using the same NAID if NAID is equal to 4294967295 (0xffffffff).
<b>Programming Impacts</b>	None
<b>Operational Impacts</b>	None
<b>Documentation Impacts</b>	None
<b>MML Help Text Impact</b>	None
<b>MO and DB File Impact</b>	None

**CRSnn17043**      **Problem configuring IPSPLIST parameter**

<b>Detailed Description</b>	While configuring an IPAS (IP Application Server) managed object, it is requested to be able to add more than 5 ipsp's which is the current limit.
<b>Solution</b>	Increase the IPSP limit that can be added for an IPAS.
<b>Programming Impacts</b>	None
<b>Operational Impacts</b>	None
<b>Documentation Impacts</b>	Yes  SGC Manual: Section 6.5.3.10 => "An IPAS can be assigned a list of up to five IPSP's" should be updated as "An IPAS can be assigned a list of up to eight IPSP's".
<b>MML Help Text Impact</b>	None
<b>MO and DB File Impact</b>	None

## CRSnn17044

### NAID parameter optional

<b>Detailed Description</b>	SG/SGC should be able to not send the NA (Network Appearance) parameter as suggested by RFC4666 section 3.3.1.
<b>Solution</b>	When NAID is set as 4294967295 (0xffffffff) in MML, SG/SGC will not send this parameter.
<b>Programming Impacts</b>	None
<b>Operational Impacts</b>	Yes. When NAID=4294967295 (0xffffffff), SG/SGC doesn't send NA field as NA field is optional.
<b>Documentation Impacts</b>	Yes.  SG Manual:  Section 5.5.1=>naid paragraph under PARAMETERS heading=> Valid values will be updated as 0-0xffffffff and this comment is to be added: When NAID=4294967295 (0xffffffff), NA field is not sent.  Section 5.5.9=>naid paragraph under PARAMETERS heading=> Valid values will be updated as 0-0xffffffff and this comment is to be added: When NAID=4294967295 (0xffffffff), NA field is not sent.  Table 5-5 in Chapter 5=> The NAID row of SGSPNA row should have the range value as 0-0xffffffff (instead of 0-0x7fffffff).  SGC Manual:  Section 7.5.4=>naid paragraph under PARAMETERS heading=> Valid values will be updated as 0-0xffffffff and this comment is to be added: When NAID=4294967295 (0xffffffff), NA field is not sent.  Section 7.5.9=>naid paragraph under PARAMETERS heading=> Valid values will be updated as 0-0xffffffff and this comment is to be added: When NAID=4294967295 (0xffffffff), NA field is not sent.  Table 7-5 in Chapter 7=> The NAID row of SGCDPC row should have the range value as 0-0xffffffff (instead of 0-0x7fffffff).  Table 7-5 in Chapter 7=> The NAID row of SGCSPNA row should have the range value as 0-0xffffffff (instead of 0-0x7fffffff).
<b>MML Help Text Impact</b>	Yes. Incorporated into the release.
<b>MO and DB File Impact</b>	None

### **CRSnn17045**

#### **ASP Process kill problem**

<b>Detailed Description</b>	ASP process keeps getting killed and dumps core (4 host cluster).
<b>Solution</b>	ASP process receives a MSG_LM_REM_AS_STATE_IND (handled by lm) but at the time this message is processed, m3uaMgr->ipasTbl is empty and getElem returns garbage. m3uaMgr->ipasTbl is empty because sync process hasn't even started yet. Solution is to set elem to NULL where appropriate thus getElem will return NULL in this case and it is already handled in the callers.
<b>Programming Impacts</b>	None
<b>Operational Impacts</b>	None
<b>Documentation Impacts</b>	None
<b>MML Help Text Impact</b>	None
<b>MO and DB File Impact</b>	None

### **CRSnn17046**

#### **ASPD core dump during cluster traffic test**

<b>Detailed Description</b>	ASP process dumps core during tests at customer's site.
<b>Solution</b>	Null pointer access is prevented in ASTable.C.
<b>Programming Impacts</b>	None
<b>Operational Impacts</b>	None
<b>Documentation Impacts</b>	None
<b>MML Help Text Impact</b>	None
<b>MO and DB File Impact</b>	None

### **CRSnn17054**

#### **Race condition, heap corruption**

<b>Detailed Description</b>	ASP process dumps core during tests at customer's site.
<b>Solution</b>	Prevent the heap corruption caused by a race condition in the SCTP library.
<b>Programming Impacts</b>	None
<b>Operational Impacts</b>	None
<b>Documentation Impacts</b>	None
<b>MML Help Text Impact</b>	None
<b>MO and DB File Impact</b>	None

**CRSnn17055**      **Failure in assigning ASPD master**

<b>Detailed Description</b>	ASP master is lost during tests at customer's site.
<b>Solution</b>	Improve the process that assigns the master ASP process (improve the re-try logic).
<b>Programming Impacts</b>	None
<b>Operational Impacts</b>	None
<b>Documentation Impacts</b>	None
<b>MML Help Text Impact</b>	None
<b>MO and DB File Impact</b>	None

**1.5.0.x**

**CRSnn16989**      **Implement the unified SG/SGC package for Solaris 8/9/10**

<b>Detailed Description</b>	Implement the unified SG/SGC package for Solaris 8/9/10.
<b>Solution</b>	Changed the building environment from Solaris 8 to Solaris 10. Put all the binaries and configuration files used on different Solaris system into package. Modified the postinstall script, and appropriate binaries and configuration files when installing. Build twice for sctp comms library and sgp/asp using native sctp and company proprietary sctp.
<b>Programming Impacts</b>	None
<b>Operational Impacts</b>	None
<b>Documentation Impacts</b>	None
<b>MML Help Text Impact</b>	None
<b>MO and DB File Impact</b>	None

**CRSnn16970**      **Uneven distribution in stream number.**

<b>Detailed Description</b>	Uneven distribution in stream number.
<b>Solution</b>	Modify the matching algorithm between SLS and stream ID. If the SLS is less than "maximum outbound streams - 1", the mapped stream ID of SLS is "SLS + 1".
<b>Programming Impacts</b>	None
<b>Operational Impacts</b>	None
<b>Documentation Impacts</b>	None
<b>MML Help Text Impact</b>	None
<b>MO and DB File Impact</b>	None



**CRSnn16976**      **Change sctp.conf parameters in run-time on Solaris 10**

<b>Detailed Description</b>	Change sctp.conf parameters in run-time on Solaris 10
<b>Solution</b>	The sgpd can change some SCTP and IP parameters dynamically for specific associations according to the sctp.conf file once it receives HUP signals.
<b>Programming Impacts</b>	None
<b>Operational Impacts</b>	None
<b>Documentation Impacts</b>	None
<b>MML Help Text Impact</b>	None
<b>MO and DB File Impact</b>	None

**CRSnn16891**      **Support database to text conversion for SG/SGC**

<b>Detailed Description</b>	Support database to text conversion for SG/SGC
<b>Solution</b>	Enhance the D7 db2text functionality for SG/SGC.
<b>Programming Impacts</b>	None
<b>Operational Impacts</b>	None
<b>Documentation Impacts</b>	None
<b>MML Help Text Impact</b>	None
<b>MO and DB File Impact</b>	None

**CRSnn15885**      **Re-dimensioned ASs/RKs on the SG side.**

<b>Detailed Description</b>	Re-dimensioned ASs/RKs on the SG side.
<b>Solution</b>	Found the parameters that limited the ASs/RKs. Examined the parameters the modifications woCRSuld impact. Adjusted the size of the ASs/RKs.
<b>Programming Impacts</b>	None
<b>Operational Impacts</b>	None
<b>Documentation Impacts</b>	None
<b>MML Help Text Impact</b>	None
<b>MO and DB File Impact</b>	None

**CRSnn15941**      **All routing key types that involve "OPC" could not be configured or applied.**

<b>Detailed Description</b>	All routing key types that involve "OPC" could not be configured or applied.
<b>Solution</b>	Traced the routing key type issues. Modified the code and then tested to make sure the routing key types supported worked fine.
<b>Programming Impacts</b>	None
<b>Operational Impacts</b>	None
<b>Documentation Impacts</b>	None
<b>MML Help Text Impact</b>	None
<b>MO and DB File Impact</b>	None

**CRSnn16247**      **aspd and sctpd are killed every some minutes on Solaris 9.**

<b>Detailed Description</b>	aspd and sctpd are killed every some minutes on Solaris 9.
<b>Solution</b>	Modified aspd and sctpd code to make sema_wait run again if returned for EINTR.
<b>Programming Impacts</b>	None
<b>Operational Impacts</b>	None
<b>Documentation Impacts</b>	None
<b>MML Help Text Impact</b>	None
<b>MO and DB File Impact</b>	None

**CRSnn16248**      **Support override mode of AS for SG/SGC.**

<b>Detailed Description</b>	Support override mode of AS for SG/SGC.
<b>Solution</b>	Modified the OAM layer code and M3ua stack layer to support the override mode and implement the override scene.
<b>Programming Impacts</b>	None
<b>Operational Impacts</b>	None
<b>Documentation Impacts</b>	None
<b>MML Help Text Impact</b>	None
<b>MO and DB File Impact</b>	None

**CRSnn16288**      **Support native sctp stack on Solaris 10 or above for SG/SGC**

<b>Detailed Description</b>	Support native sctp stack on Solaris 10 or above for SG/SGC.
<b>Solution</b>	Implemented Solaris 10 sctp protocol stack and sctp interface for users. Used sctp api functions to implement sctp comms library. Made the asp/sgp work using the new library without sctpd, then modified all the relating script including build and packit.
<b>Programming Impacts</b>	None
<b>Operational Impacts</b>	None
<b>Documentation Impacts</b>	None
<b>MML Help Text Impact</b>	None
<b>MO and DB File Impact</b>	None

**CRSnn16303**      **Support SG-SGC and SGC-SG-SGC communications.**

<b>Detailed Description</b>	Support SG-SGC and SGC-SG-SGC communications.
<b>Solution</b>	Modified the rtset state so that it would update in a SGC-SG-SGC scenario. Modified the packit script to packit isup and tcap parts for SG.
<b>Programming Impacts</b>	None
<b>Operational Impacts</b>	None
<b>Documentation Impacts</b>	None
<b>MML Help Text Impact</b>	None
<b>MO and DB File Impact</b>	None

**CRSnn16403**      **Compiler upgrade for 1.5.0.**

<b>Detailed Description</b>	Compiler upgrade for 1.5.0.
<b>Solution</b>	Upgraded the complier using different flags. Linked it to past libraries.
<b>Programming Impacts</b>	None
<b>Operational Impacts</b>	None
<b>Documentation Impacts</b>	None
<b>MML Help Text Impact</b>	None
<b>MO and DB File Impact</b>	None

**CRSnn16404**      **Support x86 platform for SG/SGC 1.5.0**

<b>Detailed Description</b>	Support x86 platform for SG/SGC 1.5.0
<b>Solution</b>	Compiled the SG/SGC on x86 platform to get x86 SG/SGC 1.5.0 package.
<b>Programming Impacts</b>	None
<b>Operational Impacts</b>	None
<b>Documentation Impacts</b>	None
<b>MML Help Text Impact</b>	None
<b>MO and DB File Impact</b>	None